

Power Quality Enhancement for Breeze Energy Conversion System Using Conservative Power Theory

Mr.Prabaakaran,M.E¹,Mr.Sri krishna kumar S,M.E²,
Ramanujam A³,Vijayakumar V⁴,Muthukumar D⁵

^{1,2}Assistant professor, ^{1,2,3,4,5}Department of EEE

Vel Tech High Tech Dr.Rangarajan

Dr.Sakunthala Engineering College

Chennai,India

prabaakaran031@gmail.com,

krishnakumar.rvs@gmail.com,

ramanujam097@gmail.com,

Vijayakumarspidy7@gmail.com,

muthujaguar@gmail.com

May 9, 2018

Abstract

An exhaustive control of a breeze turbine system associated with a industrial plant is examined in this paper, where a calculation has been created permitting a control structure that uses a 4-leg inverter associated with the network lateral to infuse the accessible vitality, and in addition to fill in as a active power filter mitigating load current disturbances and upgrading power quality. The project deals about the control method for a back-to-back breeze turbine system connected to an industrial plant. The control uses the 4-leg inverter at the network lateral sto supply available active power from the breeze turbine system along with full compensation of load current disturbances. The main contribution is based on CPT to impress the set-point reference and

impose disturbances mitigation, which adds significant flexibility to the control structure. The control structure was tested with a comprehensive real time benchmarking case-study with hardware in the loop. The control algorithms were compiled in network our controller and validated using the real-time system. The algorithms were debugged and are ready for experimental validation in a retrofitting of a breeze turbine. Therefore, the controller is intended to keep the dc voltage at constant value and provide non active compensation to improve the power quality of the network current. During this condition, the network supplies the active power for the load. When the breeze speed increases above the cut-in speed and the turbine started producing power, the network-network inverter inject the active and compensate non active components. If the produced power is more than the load power, the remaining is injected to the network.

Key Words:Conservative power theory (CPT), voltage source converter (VSC) 4-leg, equipment on the up and up (HIL), doubly fed induction generator(DFIG), control quality.

1 INTRODUCTION

The worldwide limit of introduced breeze turbines has quickly expanded over the most recent couple of years, this improvement is because of the headway in generator in electrical and hardware in power applications[1]. The principle problem with sustainable power source is that the power isn't generally accessible when it is required. The expansion of power generation of sustainable resources, utility reconciliation has been created and executed and control inverters are utilized to control active/reactive power, recurrence, and to help matrix voltage flaws and voltage sag[2]-[3]. The network lateral controllers are intended to guarantee active and reactive power is delivered to the network. In PQ theory, the 3 phase is changed into a to 2 phase reference outline so as to extract active and reactive segments in a streamlined way. A 3 phase control theory in a more extensive point of view has been introduced, known as the moderate power theory (CPT), the current and voltage segments are inferred in the 3 phase shape, without requiring any

reference outline trans arrangement. This paper proposes a control structure in 3 phase 4-wire systems that give greater usefulness to the matrix network converter of a breeze turbine system utilizing the CPT as a modify local to creating distinctive current references for specific unsettling influences remuneration, where both 1 phase and 3 phase loads are bolstered. 3 phase, 4-wire inverters has acknowledged utilizing traditional 3-leg converters with "split capacitor" or 4 leg converters.




Fig.1. 1 Line Chart Of The Tended To Modern System With Breeze Turbine System.

2 CONFIGURATION OF THE SYSTEM

Fig. 1 demonstrates a chart of an usefulness associated modern system tended to this paper. The power converter structure utilized as a part of the breeze turbine system is a consecutive converter to Doubly Fed Induction generator (DFIG) associated with a similar transport with the heaps. The heaps are a mix of direct and very nonlinear loads causing sounds at PCC [4].

3 CONSERVATIVE THEORY IN POWER

The CPT, planned through, decays the power and mongrel lease in the inactive edge, as per terms specifically identified with electrical attributes, for example, normal power exchange, re-active vitality, lop networked loads and non linearity. Accepting a nonspecific poly-phase circuit under occasional task (period T), where (v) and (I) are, individually, the voltage and current vectors, is unprejudiced essential of the voltage vector estimated at a given system port phase factors the CPT creators characterize[5].

1) active power

$$p(t) = \underline{v} \cdot \underline{i} = \sum_{m=1}^M v_m i_m. \quad (1)$$

2) Instantaneous reactive power

$$w(t) = \underline{\hat{v}} \cdot \underline{i} = \sum_{m=1}^M \hat{v}_m i_m. \quad (2)$$

The average values of (1) and (2) are the active power and reactive power defined in (3) and (4),

$$P = \bar{p} = \underline{v} \cdot \underline{i} = \frac{1}{T} \int_0^T \underline{v} \cdot \underline{i} dt = \sum_{m=1}^M P_m, \quad (3)$$

$$W = \bar{w} = \underline{\hat{v}} \cdot \underline{i} = \frac{1}{T} \int_0^T \underline{\hat{v}} \cdot \underline{i} dt = \sum_{m=1}^M W_m. \quad (4)$$

The currents in phase are decomposed into 3 current components as follows

$$i_{am} = \frac{v_m, i_m}{\|v_m^2\|} v_m = \frac{P_m}{V_m^2} v_m = G_m v_m, \quad (5)$$

G_m is phase conductance.

Reactive phase currents are

$$i_{rm} = \frac{\hat{v}_m, i_m}{\|\hat{v}_m^2\|} \hat{v}_m = \frac{W_m}{V_m^2} \hat{v}_m = B_m \hat{v}_m, \quad (6)$$

B_m is phase reactivity Void phase currents

$$\underline{i}_{vm} = \underline{i}_m - \underline{i}_{am} - \underline{i}_{rm}, \quad (7)$$

The balanced active currents are

$$\underline{i}_{am}^b = \frac{v \cdot \underline{i}}{\|\underline{v}\|^2} \underline{v}_m = \frac{P}{V^2} \underline{v}_m = G^b \underline{v}_m, \quad (8)$$

The balanced reactive currents are

$$\underline{i}_{rm}^b = \frac{\hat{v} \cdot \underline{i}}{\|\hat{v}\|^2} \hat{v}_m = \frac{W_r}{V^2} \hat{v}_m = B^b \hat{v}_m, \quad (9)$$

The imbalanced active currents are g

$$\underline{i}_{am}^u = \underline{i}_{am} - \underline{i}_{am}^b = (G_m - G^b) \underline{v}_m. \quad (10)$$

Imbalanced reactive currents are

$$\underline{i}_{rm}^u = \underline{i}_{rm} - \underline{i}_{rm}^b = (B_m - B^b) \hat{v}_m. \quad (11)$$

Thus, the total imbalance phase current vector is

$$\underline{i}_m^u = \underline{i}_{am}^u + \underline{i}_{rm}^u. \quad (12)$$

The current vector can be given as

$$\underline{i} = \underline{i}_a^b + \underline{i}_r^b + \underline{i}_a^u + \underline{i}_r^u + \underline{i}_v. \quad (13)$$

4 DESIGN CONTROL

A. MACHINE NETWORK CONTROLLER

The reason for the machine network converter is to track the optimum purpose of the rotor to extract the most extreme power existing in the turbine. For a given breeze turbine, the most extreme power happens at the greatest power coefficient of the turbine. For a given breeze speed, there is an ideal rotor speediness that gives ideal tip speed proportion[6].




Fig.2. Control Structure Of Machine Lateral Converter

$$\lambda_{\text{opt}} = \frac{R_w \omega_{w,\text{opt}}}{v_w} . \quad (14)$$

By perceptive the tip speed ratio of the breeze turbine, by computing the ideal rotor speed as


$$\omega_{w,\text{opt}} = \frac{v_w \lambda_{\text{opt}}}{R_w} . \quad (15)$$

Fig.3. Contol Scheme Of Network- Lateral Converter

At that point, this ideal rotor position is deduced from deliberate rotor speed to deliver the speed mistake. As appeared in Fig. 2, a rotor speed regulator is intended to create the quadrature current reference to the interior current regulator. The immediate current position in this paper is set to zero. The detail of the regulator plan methodology is introduced .

B. NETWORK LATERAL CONTROLLER

The inductance of the filter is L_f and R_f is the ohmic defeat of inductor. The machine lateral converter of Fig. 2 is associated in similar with VSC dc-connect capacitor C_{dc} [7]. It remains demonstrated that network lateral inverter unit is controlled in an abc-reference outline. v_p cc is managed by the network speaking to



The PCC/stack voltage. The objective of control is to permit the breeze source to infuse its accessible vitality, and to fill in as a active filter aimed at enhancing power quality in view of CPT functionalities. demonstrates the circuit, containing together adjusted and lopsided networked for linear plus nonlinear loads[8].

The inverter entity control scheme comprises of dual criticism control circles . The primary circle exhibited in Fig. 4 quick circle controlling the yield current, demonstrating that $i_{o,abcn}$ can quickly track individual allusion charges $i_{o,abcn}^*$, though io,n is resolved as

$$L_f \frac{di_{o,abcn}(t)}{dt} + R_f i_{o,abcn}(t) = v_{o,abcn}(t) - v_{pec,abcn}(t). \quad (16)$$

$$v_{o,abcn}(t) = G_{inv} m_{o,abcn}(t) = \left(\frac{V_{dc}}{2} \right) m_{o,abcn}(t). \quad (17)$$

$$G_i(s) = \frac{i_{o,abcn}(s)}{v_{o,abcn}(s)} = \frac{1}{L_f s + R_f}. \quad (18)$$

$$G_{oi}(s) = \frac{C_i(s)}{R_f + sL_f}, \quad (19)$$

$$C_i(s) = \frac{k_c (1 + s/\omega_z)}{(1 + s/\omega_p)}. \quad (20)$$

$$G_i(z) = Z \left\{ \frac{(1 - e^{-sT_s}) G_i(s)}{s} \right\}. \quad (21)$$

$$G_i(z) = (1 - z^{-1}) Z \left\{ \frac{G_i(s)}{s} \right\}. \quad (22)$$

To permit an utilization of the recurrence reaction strategy outline, the change of $G_i(z)$ exchange work from "z" plane to "w" plane is achieved utilizing bilinear change appeared in (23)

$$z = \frac{1 + \frac{T_s}{2}w}{1 - \frac{T_s}{2}w}. \quad (23)$$

From Where Comes

$$G_i(w) = \frac{-0.0041w + 100}{w + 10}. \quad (24)$$

Fig.4. Block Diagram Of Vlotage Contorl Loop

An examination between the recurrence reaction of system exchange work $G_i(s)$, plant digitalised $G_i(w)$. It stands perceptible that the recurrence reaction presents congruity by the zero included as a result of digitalisation procedure. The hybrid recurrence of the

The yield current conduct of system tied 4-leg inverter can remain depicted by (25), seen that the yield current just relies upon the position current. As such, below the sustain forward remuneration, the converter scheme is proportionate to a free current cradle as saw by AC scheme For computerized usage of control scheme in the z-area, the controller of (20) is described by the bilinear change with an inspecting period of T_s that is likewise the exchanging limit. In this way, the controller exchange work $C_i(z)$ [9].

For computerized usage of control scheme in the z-area, the controller of (20) is described by the bilinear change with an inspecting period of T_s that is likewise the exchanging limit. In this way, the controller exchange work $C_i(z)$ [9].

Can be expressed as

The present reference, $i_{active,abc}$, is utilized to infuse the Active power conveyed from the breeze through the inverter. The chart of active current position is characterized from the key part of the deliberate capacity voltage, $v_p^{f_{cc,abc}}$, arranging sinusoidal current. Along these lines, the active i is an unadulterated current in sinusoidal, in phase with the central component of the immediate load voltage. Dimensioning of dc-connect voltage controller is dictated by the exchange work between the characterized current position and dc-interface voltage.

From control adjust of the inverter fatal, we have where icapacitor dc-interface current in capacitor and $5/4s$ factor originates as normal AC power stream utilizing top esteems and $v_{pcc,abc}^f$ speaks to the crucial segment of voltage.

$$P_{ac} + P_{wind} + P_{cap} = 0. \quad (27)$$

$$\frac{3}{2} v_{pcc,abc}^f i_{active,abc} + V_{dc} I_{dc} + V_{dc} i_{capacitor} = 0. \quad (28)$$

From (28) the current through the capacitor is

$$i_{capacitor} = - \left(\frac{3v_{pcc,abc}^f i_{active,abc}}{2V_{dc}} + I_{dc} \right). \quad (29)$$

The current in capacitor

$$C_{dc} \frac{dV_{dc}}{dt} = i_{capacitor}. \quad (30)$$

Differential equation on behalf of dc-connection voltage becomes

$$\frac{dV_{dc}}{dt} = - \frac{1}{C_{dc}} \left(\frac{3v_{pcc,abc}^f i_{active,abc}}{2V_{dc}} + I_{dc} \right). \quad (31)$$

view of voltage is managed by regulatory the voltage iactive,ab c . The square outline voltage control in dc circle is appeared in Fig. 8. The dc-interface voltage controller $C_{vdc}(s)$ is increased by 1 to adjust for the reverse ssign of dc transport voltage elements.

In this way, the closed current circle can be accepted perfect for configuration purposes and supplanted by solidarity. The exchange capacities of dc-connect voltage control conspire, $G_{vdc}(s)$, is exhibited The open-circle exchange elements of the dc voltage control circle, $G_{ovdc}(s)$, is introduced in (with $C_v(s)$ the controller.

where the bounds of k_p and k_i are the relative and necessary additions of compensator, separately

$$G_{vdc}(s) = \frac{3v_{pcc,abc}^f}{2V_{dc}} \frac{1}{C_{dc}s}. \quad (32)$$

$$G_{ovdc}(s) = C_v(s) G_{vdc}(s) \quad (33)$$

$$C_v(s) = \frac{k_p s + k_i}{s}. \quad (34)$$

For PIC execution of dc-link control in voltage conspire, $G_{vdc}(s)$, is changed over from consistent plane "s" to the discrete plane "z". To permit the utilization of recurrence reaction technique outline, the change of $G_{vdc}(z)$ transfer work from "z" plane to "w" plane is performed spending the bilinear change




Fig.5. Block Diagram Of Current Control Loop

The hybrid recurrence of the dc voltage circle is been $f_{cvdc} = 50\text{Hz}$ and phase edge ϕ_{PMvdc} is chosen to be 60° . We should register that $k_p = 0.59$ and $k_i = 13.12$. Fig. 9 demonstrates the recurrence reaction of the open-circle dc-connect control plot in voltage. This one seen that at traverse recurrence, the exposed circle pick up of 0 dB and the phase edge of 60 are gotten. The dc-interface controller in voltage $C_v(s)$ is additionally discretized for computerized usage utilizing the bilinear change with testing period of T_s namely the exchanging time frame. In this way, the controller exchange work $C_v(z)$ can be communicated as takes after

$$C_v(z) = \frac{0.6z - 0.6}{z - 1}. \quad (37)$$




Fig .6. Active Power And Reactive Power Delivery

The proposed modern system with the breeze turbine appeared as displayed and ordered utilizing the notable continuous test system RT. RT permits exact seat checking of continuous controllers, with particular examining for particular control squares.

The DFIG parameters utilized as a part of the prototypical from [3]. The particular of the breeze turbine was chosen in accord to such parameters.

A. ACTIVE AND REACTIVE POWER DELIVERY

The regulator is set to stream the adjust reactive current/control segment of the heap other than conveyance of power in active ($i_{ref} = i_{active} + i_{br}$). Since the voltage and current waveforms appeared in the inverter is providing power in active and reactive since the current in inverter is never again in phase with the voltage. The after effect pay methodology is appeared in which the void and unbalance current parts of sheap is provided by matrix. It can be seen from the network is providing nonpartisan present, identified with 1 phase load[12]-[13].

5 CONCLUSION

This paper give a lecture of complete manipulate approach for a back-to- back breeze turbinegadget linked to the commercial plant. The controller makes use of 4-leg inverter on the network aspect to supply accessible lively electricity from the breeze turbine machine in conjunction with complete compensation of load cutting-edge disturbances. The primary contribution is primarily established on CPT to affect the set-factor reference and impose disturbances mitigation, which provides giant flexibility to the manipulate shape.

The control arrangement changed into tested with a complete actual-time benchmarking case-study with hardware within the loop. The control algorithms had been compiled internal our PIC and validated the usage of the actual-time gadget RT. The algorithms had been corrected and are prepared for experimental validation in retrofitting of a breeze turbine. The outcomes support the gadget offered here that could keep away from installation of lively filter hardware via the software either by means of commercial purchaser.

References

- [1] Global breeze r report annual market update 2013, 2013. [Online]. Avail-able: <http://www.gwec.net>
- [2] S. Li, T. A. Haskew, R. P. Swatloski, and W. Gathings, Optimal and direct-current vector control of direct-driven DFIG

- breeze turbines, *IEEE Trans. Power Electron.*, vol. 27, no. 5, pp. 23252337, May 2012.
- [3] N. Angela, M. Liserre, R. A. Mastromauro, and A. D. Aquila, A survey of control issues in DFIG-based, *IEEE Trans. Ind. Informat.*, vol. 9, no. 3, pp. 12111221, Aug. 2013.
- [4] J. Lagorse, M. G. Simoes, and A. Miraoui, A multiagent fuzzy-logic-based energy management of hybrid systems, *IEEE Trans. Ind. Appl.*, vol. 45, no. 6, pp. 21232129, Nov./Dec. 2009.
- [5] X. Tan, Q. Li, and H. Wang, Advances and trends of energy storage technology in micronetwork, *Int. J. Elect. Power Energy Syst.*, vol. 44, pp. 179191, Jan. 2013.
- [6] P. F. Ribeiro, B. K. Johnson, M. L. Crow, A. Arsoy, and Y. Liu, Energy storage systems for advanced power applications, *Proc. IEEE*, vol. 89, no. 12, pp. 17441756, Dec. 2001.
- [7] M. G. Simoes, B. K. Bose, and R. J. Spiegel, Fuzzy logic based intelligent control of a variable speed cage machine breeze generation system, *IEEE Trans. Power Electron.*, vol. 12, no. 1, pp. 8795, Jan. 1997.
- [8] A. Chauhan and R. P. Saini, A review on integrated renewable energy system based power generation for stand-alone applications: Configurations, storage options, sizing methodologies and control, *Renew. Sustain. Energy Rev.*, vol. 38, pp. 99120, Oct. 2014.